A COIN DISCRIMINATING DEVICE AND METHOD, AND A COIN HANDLING MACHINE INCLUDING SUCH A DEVICE AND METHOD

Technical Field

The present invention relates to a device and a method for coin discrimination or validation. More specifically, the invention relates to coin discrimination or validation by using capacitive coupling between the coin and a sensor device for determining the thickness of the coin. The invention also relates to a coin handling machine, in which the device and method are used.

Background Art

Coin discriminators are used for measuring different physical characteristics of a coin in order to determine its type (e.g. its denomination, currency or authenticity). Various dimensional, electric and magnetic characteristics are measured for this purpose, such as the thickness and diameter of the coin, its electric conductivity and its magnetic permeability. Coin discriminators are commonly used in coin handling machines, such as coin counting machines, coin sorting machines, vending machines, gaming machines, etc. Examples of previously known coin handling machines are for instance disclosed in WO97/07485 and WO87/07742.

Starting with the electric characteristics of coins, EP-B-300,781 and EP-B-0,119,000 describe previously known ways of measuring coin conductivity. A transmitter coil is driven with a pulsed supply voltage so as to generate a magnetic pulse, which is induced in a coin, which moves along a coin path or rail past the transmitter coil. The eddy currents thus generated in the coin in turn produce a magnetic field, which is monitored or detected by a receiver coil. The receiver coil may be a separate coil or may alternatively be constituted by the transmitter coil

itself having two operating modes. By monitoring the decay
of the eddy currents induced in the coin, a value represen-
tative of the coin conductivity may be obtained, since the
rate of decay is a function thereof. A coin discriminator
5   of a similar type, albeit especially adapted for bimetallic
coins, is disclosed in WO99/39311.

As regards the magnetic characteristics of coins,
e.g. their magnetic permeability, US-A-4,483,431 relates to
a coin discriminator, where a permanent magnet and a Hall
10 effect device is used for checking the magnetic properties
of the coin, when it passes the Hall effect device. More-
over, US-A-5,119,916 discloses a sensor for validating sub-
way tokens. The sensor has two pairs of permanent magnets
and Hall effect sensors, which determine the magnetic
15 characteristics (and consequently the permeability) of
the respective token.

Various methods are known for determining the coin
diameter in coin discriminators. According to PCT
GB88/00592 a coin is exposed to high-frequency magnetic
20 pulses from a pair of coils. When the coin passes the
coils, the magnetic field is shielded, and a pickup coil
is used for determining the coin diameter in response to
this momentary shielding. Alternatively, the coin diameter
may be determined optically by using a line of optical
25 detectors located opposite a light source. When a coin
passes between the optical detectors and the light source,
a certain number of the optical detectors are momentarily
shielded or cut off by the passing coin. The coin diameter
follows immediately from the number of shielded optical
30 detectors.

Also the coin thickness may be determined by optical
arrangements similar to the one described above for mea-
suring the coin diameter. Alternatively, as disclosed in
EP-B-300,782, an ultrasound detector may be used for deter-
35 mining the thickness of a coin. Furthermore, EP-A-343,871

discloses a capacitive coin validation method, involving
a pair of electrode assemblies on either sides of a coin
path. Most specifically, in EP-A-343,871 the pair of elec-
trode assemblies comprises sensor electrodes and guard ring
5   electrodes that are disposed on either sides of the coin
path. The sensor electrodes are driven with an oscillating
signal from dual resonant circuits, so that when a coin
passes the electrodes during the validation thereof, the
inter-electrode capacitance is altered. Thus, in effect,
10   the sensor electrodes act as first and second capacitor
plates that form a capacitor, the capacitance of which is
changed by the presence of the coin. Thereby, also the
resonating signals from the resonant circuits are changed.
In EP-A-343,871, the coin must be electrically isolated
15   from the electrode assemblies, thereby requiring electrical
isolation in the coin path.

Thus, the device in EP-A-343,871 requires an electri-
cally isolated coin path and, moreover, first and second
capacitor plates (the electrode assemblies) placed on
20   either side of the coin path.

Summary of the Invention

It is an object of the present invention to provide
an improved coin discriminating device and method for
25   capacitive determination of coin thickness. In particular,
the invention seeks to allow such coin discrimination
through capacitive determination of coin thickness with
less components and improved reliability compared to the
prior art.
30   The objects of the invention are achieved by a coin
discriminating device, a coin discriminating method and
a coin handling machine according to the attached inde-
pendent patent claims.

Other objects, features and advantages of the present
35   invention will appear from the following detailed

4

disclosure of a preferred embodiment, from the enclosed
drawings as well as from the subclaims.

Brief Description of the Drawings

5   A preferred embodiment of the present invention will
now be described in more detail, reference being made to
the accompanying drawings, in which:

FIG 1 is a schematic top view of a coin discrimi-
nating device according to the invention and a part of

10   a coin transport mechanism,

FIG 2 is an enlarged sectional view of a portion
of the device and mechanism shown in FIG 1,

FIG 3 is a schematic block diagram of a preferred
embodiment of the coin discriminating device,

15   FIG 4 is a flowchart diagram illustrating a coin
discriminating method according to the preferred embodi-
ment, and

FIG 5 is a schematic block diagram of a coin hand-
ling machine according to the invention.

20

Detailed Disclosure of a Preferred Embodiment

FIG 1 illustrates a coin discriminator 3 having a
coin discriminating device 4, 5 for determining, by capa-
citive coupling, the thickness of each individual coin 1

25   when transported past a sensor electrode 5. FIG 1 also
shows some parts of a coin transport mechanism, which is
adapted to transport each coin 1 along a circular path,
in a rotational direction A, past the coin discriminator
3 and, specifically, the sensor electrode 5. The coin

30   discriminator 3 and the coin transport mechanism are
illustrated in more detail in FIG 2. As regards the
coin transport mechanism, an advantageous implementation is
thoroughly described in published PCT applications
PCT/SE98/02406 and PCT/SE00/00189, both of which are fully

incorporated herein by reference. However, the invention is
not limited to this kind of coin transport mechanism.

Briefly, the coin transport mechanism operates as
follows. Coins to be discriminated are deposited onto the
5   center region of an essentially flat rotating disc 11.
The stationary ring is arranged immediately above the
rotating disc 11 with only a minimum gap between the two,
without actually reaching contact therewith. A rotating
ring 2 is mounted to the outside of the stationary ring. On
10 the underside of the rotating ring 2 there is provided a
resilient rim 10. The rotating ring 2 is biased towards the
rotating disc 11, so that the resilient rim 10 will
frictionally engage the upper surface of the rotating
disc 11, thereby forcing the periphery of the rotating
15 disc 11 to rotate at the same speed as the rotating ring 2,
when the latter is driven by means of e.g. an electric
motor and a drive belt.

As the rotating disc 11 is rotated in direction A,
the coins deposited onto the disc are accelerated by the
20 centrifugal force in a radial direction towards the sta-
tionary ring. Then, the coins are driven through an opening
in the stationary ring and are forced into contact with the
inside of the resilient rim 10 on the rotating ring 2. A
thin stationary edge or knife is provided on the underside
25 of the stationary ring with a minimum gap to the upper
surface of the rotating disc 11. The purpose of the
stationary edge or knife is to peel off a single layer of
coins, which are engaged between the resilient rim 10 and
the rotating disc 11, as illustrated by the coin 1 in
30 FIG 2. Thus, as shown in FIG 1, the coins are engaged at
their periphery between the resilient rim 10 and the rota-
ting disc 11 and are accurately transported, essentially
without friction or other energy losses, along their cir-
cular sorting path.

As already mentioned, the coin discriminator 3 includes a capacitive-type thickness detector, which is indicated at 4 and 5 in FIG 1 and at 4, 5, 6, 7, 8, 9 and 12 in FIG 2. In addition, the coin discriminator 3 may advantageously also include further sensors for detecting other properties of the coin 1 than its thickness, such as electrical conductivity, magnetic permeability and diameter. However, such additional sensors are not described further herein.

As shown in FIG 2, the capacitive-type coin discriminating device (coin thickness detector) is based on a dual-layer circuit board 9 having electronic circuitry 12 mounted thereon. The electronic circuitry is illustrated in more detail in FIG 3. The circuit board 9 rests on a rigid glass fiber laminate 4, which in turn is attached to a base socket 8 to be securely mounted onto the coin discriminator 3. On its lower surface, the glass fiber laminate layer 4 is provided with the sensor electrode 5, which acts as one capacitor plate, as will be described in more detail in the following, and is electrically coupled, at 7, to the electronic circuitry 12 on top of the circuit board 9. The surface of the sensor electrode 5 is covered by a thin insulating layer 6. As shown in FIG 2, the coin discriminator 3 and the capacitive coin thickness detector mounted thereon form an intermediate gap, which is large enough for allowing the coin 1 to pass safely in between, without physical contact, when carried along the circular path by the rotating ring 2 and the rotating disc 11.

The general principle of the coin discriminating device according to the invention is that there exists a relation between the position of the upper surface of the coin 1 and the thickness of the coin 1. To this end, the position of the upper coin surface is measured by the sensor electrode 5, in the form of a distance x, through a capacitance C_m, which is generated between the upper

surface of the coin 1 and the sensor electrode 5. Thus, the
sensor electrode 5 will act as a first capacitor plate,
whereas the upper surface of the coin 1 will act as a
second capacitor plate. Since the lower surface of the

5 coin 1 will always be in the same position in relation to
the sensor electrode 5 (thanks to the fixed arrangement of
the coin transport mechanism 2, 10, 11), it is possible to
determine the thickness of the coin. With reference to
FIG 3, the capacitance C_m between the sensor electrode 5

10 and the upper surface of the coin 1 is determined by the
electronic circuitry 12 in the following way.

A voltage-controlled oscillator (VCO) 13 is used as a
first signal-producing element. To pre-set the frequency
operating range of the VCO 13 a voltage-variable reactance

15 is used, such as a BB804 VHF variable capacitance double
diode from Philips Semiconductors, Marketing & Sales Com-
munications, Building BE-p, P.O. Box 218, 5600 MD Eind-
hoven, The Netherlands. However, any suitable tuning diode
might be used. When the tuning diode is used in the reso-

20 nant circuit of the VCO 13, the capacitance of the diode
together with the rest of the elements in the resonant
circuit will form a total reactance, which matches the
frequency of the desired VCO 13 output signal. The fre-
quency operating range of the VCO 13 is then adjusted by

25 applying a control voltage $V_{vco\text{-}ctrl}$ at a VCO control termi-
nal 14.

However, the frequency of the VCO 13 is not only
determined by the tuning diode and the control voltage.
The capacitance C_m, which is formed by the sensor elec-

30 trode 5 and the coin 1, is coupled to the resonant cir-
cuit of the VCO 13 and thus affects its output frequency.
As is well known, the capacitance value of a capacitor is
a function of the distance between the capacitor plates.
Therefore, the capacitance will increase as the distance

35 between the plates decreases. Consequently, since the lower

surface of the coin 1 is at a fixed distance from the
sensor electrode 5, the distance x between the upper side
of the coin 1 and the sensor 5 will vary depending on the
thickness d of the coin. This will result in that the
5 output frequency of the VCO 13 will vary as a function of
the thickness of the tested coins.

The output frequency of the VCO 13, f_{VCO}, is then
compared with the frequency of a fixed reference oscillator
15, f_{ref}, such as a SG8002CA programmable high frequency
10 crystal oscillator from EPSON Electronics America Inc., 150
River Oaks Parkway, San Jose, CA 95134. The above-mentioned
oscillator is by no means the only suitable oscillator for
this invention. Since it is important that the reference
oscillator 15 is frequency stable, a crystal oscillator is
15 preferably used as reference oscillator 15. Through the
rapid development of semiconductor technology, numerous
semiconductor manufacturers provide high quality
oscillators at reasonable prices.

The comparison between the output frequency of the
20 VCO 13, f_{VCO}, and the reference oscillator 15, f_{ref}, is
carried out by a mixer 16, such as a SA602A from Philips
Semiconductors, which produces the sum and difference of
the two frequencies, $f_{VCO} +/- f_{ref}$. The theory of operation
of a mixer is well known to those skilled in the art and is
25 thoroughly described in the literature, for instance
in chapter 7-2 of "Electric Communication Techniques", by
Paul H. Young, Macmillan Publishing Company, 113 Sylvan
Avenue, Englewood Cliffs, New Jersey 07632, ISBN 0-02-
431201-0.
30 To be able to separate the various frequency compo-
nents being the result of the mixing operation, the mixer
output signal passes through a low pass filter 17, which at
its output will provide a signal 18 with the frequency $\Delta f =$
$f_{VCO} - f_{ref}$.

This signal 18 is then amplified by an amplifier 19, which may be built from discrete components. The preferred embodiment uses the well known common emitter (CE) amplifier topology, based on a single transistor such as a BC817

5   from Philips Semiconductors. However, many different amplifier topologies may be used for this amplifier, such as differential amplifier topology or bootstrap amplifier topology, as is well known to a person skilled in the art. Alternatively, an operational amplifier may be used as long

10   as the maximum frequency that the operational amplifier can handle is greater than the bandwidth of the output signal of the low pass filter 17.

Since the amplifier 19 is a linear element, the output signal 20 from the amplifier 19 is a signal 20 with the

15   same frequency, Δf, as the input signal 18 but with larger amplitude. The signal 20 is then transformed by a zero crossing detector 21 into a square wave 22 with the same fundamental frequency as the amplifier output signal 20. The zero crossing detector 21 may be made up from a Schmitt

20   trigger circuit, such as a 74HC14 from Philips Semiconductors, among others, or alternatively from an ordinary comparator circuitry which is thoroughly described in for instance chapter 6 of "Operational Amplifiers with linear Integrated Circuits", by William D. Stanley,

25   Prentice Hall, Inc, Englewood Cliffs, New Jersey 07632, ISBN 0-02-415556-X. The main task of the zero crossing detector 21 is to act as an interface circuit between the amplifier and a CPU 23.

The CPU used in the preferred embodiment of the

30   invention is part of the C166 family from Infineon Technologies Corp., 1730 North First St., USA-San Jose, CA 95112. However other suitable processors may be used. The CPU 23 has an associated memory 24, preferably a nonvolatile memory such as a PROM, EPROM, EEPROM or flash

35   memory. The memory 24 stores various calibration, norma-

lization and coin reference data, which are needed in order
to determine a thickness of the coin 1 from the deviation
Δf from the idle frequency f_{VCO} of the VCO 13. As already
explained, the frequency deviation Δf is a function of the
5   capacitance C_m, which in turn depends on the distance x
between the sensor electrode 5 and the upper surface of the
coin 1 and, thus, the thickness of the coin 1. To this end,
the memory 24 stores coin reference data which provide a
mapping between frequency deviations Δf and coin thickness
10 in e.g. mm.

An outline of the operational steps of the coin
thickness detector described in the previous drawings is
given in the form of a coin thickness detection procedure
100 in FIG 4. In a first step 101, the coin thickness
15 detector may be calibrated, by making use of prestored
calibration data in the memory 24, so as to compensate
for differences in temperature, etc. Step 102 represents
the transport of the coin 1 by the coin transport mecha-
nism 2, 10, 11 to the measurement position in alignment
20 with the sensor electrode 5. The reference signal f_{ref} from
the reference oscillator 15 is generated in a step 103a,
and, simultaneously, the output signal f_{VCO} from the VCO 13
is generated in a step 103b. The two signals are mixed by
the mixer 16 in a step 104, and the result thereof is fil-
25 tered and amplified, by components 17 and 19, respectively,
in steps 105 and 106. Then, the Schmitt trigger 21
transforms the output signal 20 from the amplifier 19 into
the square wave signal 22 having, still, the fundamental
frequency Δf. In steps 108-110 the CPU 23 normalizes the
30 signal 22 and compares the normalized signal with the pre-
stored reference data in memory 24 so as to finally deter-
mine the thickness of the coin 1 in step 110. The deter-
mined thickness value is reported to the coin discrimi-
nator 3, which may use the determined thickness value in
35 combination with other coin parameters so as to determine a

type of the coin 1. As is well known per se, a coin type in
this respect may relate to denomination, currency,
authenticity, etc.

Referring now to FIG 5, a coin handling machine 200
5   is illustrated according to one aspect of the present in-
vention. In an exemplifying but non-limiting sense, the
coin handling machine 200 is assumed to be a coin sorter.
However, the coin handling machine 200 may equally well
be a coin counter, a vending machine, a gaming machine,
10   an automatic teller machine (ATM), a machine for testing
coin quality or for identifying counterfeit coins, etc.

A mass of coins to be sorted by the machine 200 are
deposited into a coin inlet 210. The coins are fed by a
coin feeder 220, such as a hopper and/or an endless belt,
15   to the coin discriminator 230, which has been described
above under reference numerals 3-9 and 12 with reference
to FIGs 1-4. The coin discriminator 230 is operatively con-
nected to a logic controller device 232 in the form of a
CPU or the like, which is operatively connected to a memory
20   234, such as a RAM, ROM, EEPROM and/or flash memory. The
CPU 232 and memory 234 are responsible for the overall
operation of the coin handling machine 200 but may also
implement some of the functionality of the coin discrimi-
nator 3-9, 12.

25   The coin handling machine 200 also comprises a coin
reject device 240, which delivers rejected coins through an
external opening in the machine 200, so that these coin may
be collected by a user of the machine. As described above,
rejected coins are determined through the coin discrimi-
30   nator. Once the type, denomination, currency, identity,
authenticity, etc, of the coin 1 has been determined by the
coin discriminator, the coin 1 is passed to a coin sorter
250, which uses the identified coin type to sort the coin 1
into one specific coin receptacle in a coin storage 260.

The coin receptacles in the coin storage 260 are preferably externally accessible for the user of the machine 200.

In an alternative embodiment, the coin discriminator 3 may advantageously be provided with a second sensor elec-
5   trode, which is mounted on the opposite side of the coin surface 1, i.e. below the coin 1 in the drawings. Addition-
ally, this second sensor electrode 6 is coupled to its own instance of the electronic circuitry 12, so that the sensor electrodes 5 and 6 independently of each other, in conjunc-
10   tion with their respective electronic circuitry 12, may produce a value of the distance x between the first sensor electrode 5 and the upper coin surface, and a corresponding distance between the second sensor electrode and the lower surface of the coin 1. This will allow an accurate deter-
15   mination of coin thickness, even in a situation where the coin is not perfectly horizontally aligned with the first and second sensor electrodes.

In yet an alternative embodiment, the coin discrimi-
nator 3, 230 may use the capacitive-type coin coin thick-
20   ness detector in conjunction with another detected coin parameter, such as coin conductivity or permeability, so as to detect the presence of a non-coin object, made of for instance plastics. It has been observed by the present inventor that even a non-metallic object will cause a de-
25   tectable frequency deviation Δf, which may be used as an indication that a non-coin object is present in front of the coin discriminator 3, since, in this situation, the other coin parameter (e.g. conductivity or permeability) will not indicate any presence of an object at all, pro-
30   vided that such object is non-metallic. Once the presence of such a non-coin object has been detected, the object may be rejected through the coin reject device 240.

The invention has been described above with reference to a few embodiment examples. However, other embodiments
35   than the ones described above are possible within the scope

of the invention, as defined by the appended independent
patent claims.

In particular, it is emphasized that the different
exemplary components of the coin discriminator of FIGs 1-4
5   as well as the components of the coin handling machine 200
of FIG 5 are only to be regarded as examples and may be
substituted by other components, as is readily realized
by a man skilled in the art of coin discrimination and
processing.

10   Finally, the term "coin" is to be interpreted as hav-
ing the widest possible meaning. Thus, objects similar to
monitary coins are intended to fall under the term "coin"
used in this patent application. Such other objects include
for instance tokens, markers, etc.

15